



SCAN AND VISIT
OUR WEBSITE



GDA6500E

GASOLINE GENERATOR/ GENERADOR A GASOLINA



6.2 KVA

MAX. POWER



ENGINE
POWER
6.2 KVA

AVR

AUTOMATIC
VOLTAGE
REGULATOR



40 L
FUEL TANK
CAPACITY

Motor: Single-cylinder, 4-stroke, air-cooled

Frequency: 110&220 V / 60 Hz

Speed: 3.600 rpm

Rated power: 5.6 KVA

Max. power: 6.2 KVA

Displacement: 420 cc

Fuel tank capacity: 40 L

Oil tank capacity: 1.1 L

Starting system: Electric start

Stator: 140 mm, Φ 32 frame

Coil material: Aluminium wire

Measures (L/D/H): 70/52,5/56,5 cm

Weight: 85 kg

Include: Handle and wheels



SCAN AND VISIT
OUR WEBSITE



GDA6500E

GASOLINE GENERATOR/ GENERADOR A GASOLINA



6.2 KVA

POTENCIA MÁXIMA



POTENCIA
DEL MOTOR
6.2 KVA



REGULADOR
DE VOLTAJE
AUTOMÁTICO



40 L
CAPACIDAD
DEL
TANQUE DE

Motor: Monocilíndrico, 4-tiempos,
refrigerado por aire

Frecuencia: 110&220 V / 60 Hz

Velocidad: 3.600 rpm

Potencia nominal: 5.6 KVA

Potencia máxima: 6.2 KVA

Cilindrada: 420 cc

Cap. tanque de combustible: 40 L

Cap. tanque de aceite: 1.1 L

Sistema de arranque: Eléctrico

Estató: 140 mm, eje $\Phi 32$

Material del bobinado: Alambre de aluminio

Medidas (L/P/A): 70/52,5/56,5 cm

Peso: 85 kg

Incluye: Manija de agarre y ruedas